arXiv:quant-ph/0206011v1 3 Jun 2002

Classical and Quantum Oscillators of Sextic and Octic Anharmonicities

Anirban Pathak and Swapan Mandal

Department of Physics
Visva-Bharati
Santiniketan-731235,
INDIA

Abstract

Classical oscillators of sextic and octic anharmonicities are solved analytically up to the linear power of λ ($Anharmonic Constant$) by using Taylor series method. These solutions exhibit the presence of secular terms which are summed up for all orders. The frequency shifts of the oscillators for small anharmonic constants are obtained. It is found that the calculated shifts agree nicely with the available results to-date. The solutions for classical anharmonic oscillators are used to obtain the solutions corresponding to quantum anharmonic oscillators by imposing fundamental commutation relations between position and momentum operators.

1 Introduction:

The basic understanding of Physics is based on some physical models. The simple harmonic oscillator (SHO) is perhaps the most useful one among them. A particle subject to a restoring force proportional to its displacement gives rise to the model of a SHO. The Hamiltonian corresponding to a classical SHO of unit mass and unit frequency is given by

$$H = \frac{p^2}{2} + \frac{x^2}{2} \tag{1}$$

and the Hamilton's equations are

$$\begin{array}{rcl} \dot{p} & = & -\frac{\partial H}{\partial x} = -x \\ \dot{x} & = & \frac{\partial H}{\partial p} = p \end{array} . \tag{2}$$

The equation of motion of the SHO is

$$\ddot{x} + x = 0 \tag{3}$$

where, equation (2) is used. Now the solution of the equation (3) is found to be

$$x_0(t) = x(0)cost + \dot{x}(0)sint. \tag{4}$$

The parameters $x(0)$ and $\dot{x}(0)$ are the initial position and momentum of the oscillator. Thus the position of the oscillator at a later time t is completely known in terms of the initial position and momentum. Nevertheless, the momentum is also known from the Hamilton's equations (2). Hence, the oscillator problem is completely solved.

The equation of motion of a quantum SHO may simply be obtained by imposing x and $\dot{x}$ as noncommuting operators. To avoid confusion, we represent the operators as capital letters instead of lowercase letters. Thus the noncommuting position and momentum operators obey the following relation

$$[X(t), \dot{X}(t)] = i \tag{5}$$

where $\hbar = 1$. The solution of a quantum SHO in Heisenberg picture is the operator equivalent of the equation (4). Now for real physical problems, the anharmonicity and/or damping are to be incorporated in the model Hamiltonian and hence in the equation of motion. However, the present letter takes care the anharmonicity only. The general form of the Hamiltonian of an anharmonic oscillator (having unit mass and unit frequency) of even order of anharmonicity is given by

$$H = \frac{p^2}{2} + \frac{x^2}{2} + \frac{\lambda}{2m}x^{2m} \tag{6}$$

where $m\,(\geq 2)$ is an integer and λ is the anharmonic constant. Depending upon the problem of physical interests, different type of anharmonic oscillators will appear. For $m = 2$, the corresponding oscillator is called quartic anharmonic oscillator. Similarly, $m = 3$ and $m = 4$ give rise to the sextic and octic anharmonic oscillators respectively. Of course, the anharmonic constants λ are different for different type of anharmonic oscillators. The equation of motion corresponding to the Hamiltonian (6) is

$$\ddot{x} + x + \lambda x^{2m-1} = 0. \tag{7}$$

where the equation (2) is used.

2 Quartic Oscillator: Brief Review.

The problem of classical and quantum anharmonic oscillators have already been studied by several authors. To begin with, we recall the problem of a classical quartic oscillator (Duffing oscillator). The equation (7), for $m = 2$, does not have exact solution. However, large number of approximate methods are available for the purpose of getting analytical solutions to the Duffing oscillator problem. These include perturbation technique [1], variation of parameters [2] and Taylor series approaches [3]. The ordinary perturbation technique, a pedestrian approach, leads to the unwanted secular terms [1]. The removal of secular terms from the solution is a serious problem. There are some methods which are successfully used to summed up the secular terms for all orders. These include "tucking in technique" [4], multiscale perturbation theory and renormalization technique[1].

The search for the solutions of anharmonic oscillators enriched different brunches of Physics and Mathematics, for example, it is successfully used to enrich the subject of large order perturbation theory [5-10], divergent expansion of quantum mechanics [11-13], Laplace transformation representation of energy eigenvalues [14] and computational physics [15-18].

The solutions of quantum quartic anharmonic oscillators may be obtained in two different pictures. The Schroedinger picture deals with the time development of the wave function. On the other hand, the time development of operators are obtained in the Heisenberg picture. Basically, the Schroedinger picture is used to solve the quantum oscillators as eigenvalue problems. In these problems, energy eigenvalues are expressed as the sum of different orders of anharmonic constant λ. The energy eigenvalues are found to diverge for large anharmonic constant. In case of small λ, however, the eigenvalues for different orders are summed up and the convergence of these sums are ensured by the Borel summability [13,19] and/ or Stieljet conditions [7].

The c-number approach to the quantum oscillator problem is found very successful but the situation is different with the operator approach. Actually, the noncommuting nature of the operators (5) pose a serious difficulty for the purpose of getting approximate solutions to the quantum anharmonic oscillator problems. Only few methods are available to-date. Aks [20]and Aks and Caharat [21] first obtained an operator solution of a quantum quartic anharmonic oscillator by using the method of Bogoliubov and Krylov. But the recent interest in the problem started with the work of Bender and Bettencourt [22-23] who obtained the solution of a quantum quartic anharmonic oscillator by using multiscale perturbation theory (MSPT). Later on Mandal[24] proposed a Taylor series approach, Egusquiza and Basagoiti[25] developed renormalization technique, Kahn and Zarmi[26] used a near identity transform method to solve the quantum quartic anharmonic oscillator problem. The Taylor series approach is found to be more successful compared to the other approaches for the purpose of getting second or higher order solution of a quantum quartic anharmonic oscillator [27].

In addition to the quartic oscillator, people have studied the higher anharmonic oscillators also [15, 28-30]. These studies are made to obtain the eigenvalues as function of anharmonicity. More recently Pathak [31] used a normal ordering technique to obtain a zeroth order multiscale perturbation theoretic solution of $m-th$ anharmonic oscillator and Fernandez[32] developed an eigen value approach to construct first order correction to the frequency operator for $m-th$ anharmonic oscillator. However, a first order solution of higher anharmonic oscillators in the realm of Heisenberg approach are yet to come. Keeping that in mind, the present letter will take care the analytical solutions of classical and quantum oscillators of sextic and octic anharmonicities. These oscillators have potential

applications in the studies of nonlinear mechanics, molecular physics, quantum optics and in the field theory. This is the first time we give analytical solution of sextic and octic oscillators under the operator formalism. The solutions are used to obtain the frequency shifts of sextic and octic oscillators. The computed shifts are compared and found to have exact coincidence with the frequency shifts calculated by using a first order perturbation theory and frequency operators obtained by Pathak [31].

3 Sextic Oscillator.

For $m = 3$, the Hamiltonian (6) and the equation of motion (7) correspond to the case of a sextic anharmonic oscillator. The solution for such an oscillator is obtained as the sum of different orders of anharmonicities. The corresponding solution is

$$x(t) = x_0(t) + \lambda x_1(t) + \ldots \tag{8}$$

where, $x_0(t)$ and $x_1(t)$ are zeroth and first order solutions respectively. The zeroth order solution (4) is simply obtained for $\lambda = 0$ in equation (7). The purpose of the present section is to find the first order solution $x_1(t)$. The lower case $x(t)$ and $\dot{x}(t)$ are to be treated as time developments of position and momentum of the classical sextic anharmonic oscillator. The equivalent operator representations are to be made by using upper case letters $X(t)$ and $\dot{X}(t)$. Thus the solution of the classical sextic anharmonic oscillator is given by the following Taylor series

$$x(t) = x(0) + t\dot{x}(0) + \frac{t^2}{2!}\ddot{x}(0) + \ldots \tag{9}$$

Here we assume that t is sufficiently small and a series (9) expansion is possible. Now we express higher order time derivatives of $x(t)$ at $t = 0$ as

$$\begin{aligned}
x^{iii}(0) &= -\dot{x}(0) - 5\lambda x^4(0)\dot{x}(0) \\
x^{iv}(0) &= x(0) + 6\lambda x^5(0) - 20\lambda x^3(0)\dot{x}^2(0) \\
x^{v}(0) &= \dot{x}(0) + 70\lambda x^4(0)\dot{x}(0) - 60\lambda \dot{x}^3(0)x^2(0) \\
\ldots &\quad \ldots \quad \ldots \\
\ldots &\quad \ldots \quad \ldots
\end{aligned} \tag{10}$$

where, we have neglected λ^2 and higher order terms. We substitute the relations (10) in equation (9) to collect the coefficients of $x^5(0)$, $x^4(0)\dot{x}(0)$, $x^3(0)\dot{x}^2(0)$, $x^2(0)\dot{x}^3(0)$, $x(0)\dot{x}^4(0)$ and $\dot{x}^5(0)$ (without the constant multiplication factor λ). Corresponding coefficients are

$$\begin{aligned}
C_0 &= -(1 - 6 + 71 - 1276 + 27741 - 656546 + \ldots) \\
C_1 &= -(5 - 70 + 1275 - 27740 + 656545 - \ldots) \\
C_2 &= -(20 - 460 + 10680 - 258920 + 6399340 - \ldots) \\
C_3 &= -(60 - 1860 + 49320 - 12577720 + 31664580 + \ldots) \\
C_4 &= -(120 - 4320 + 120240 - 3116640 + 78912360 - \ldots) \\
&and \\
C_5 &= -(120 - 4320 + 120240 - 3116640 + 78912360 - \ldots)
\end{aligned} \tag{11}$$

where the coefficient of $x^{5-i}(0)\dot{x}^i(0)$ is denoted by C_i. The contributions directly from Taylor expansion are not taken into consideration. The $r-th$ term of C_0 is given by

$$t_r^{/} = (-1)^r \times \tfrac{1}{384}\left(25^r + 15 \times 9^r + 240r - 16\right). \tag{12}$$

Now we can write the $r-th$ term of the coefficient of $x^5(0)$ in $x_1(t)$ as

$$t_r = t_r^{/} \times \frac{t^{2r}}{(2r)!}, \tag{13}$$

where the factor $\frac{t^{2r}}{(2r)!}$ comes from the Taylor expansion part. The net coefficient of $x^5(0)$ in $x_1(t)$ is obtained as

$$K_0 = \sum t_r = \frac{1}{384}(cos5t + 15\,cos3t - 16\,cost - 120\,tsint). \tag{14}$$

The parameter K_0 exhibits fifth and third harmonic generations along with the secular term proportional to $t\,sint$. The secular terms are responsible for the divergent nature of the solution. This is an uncomfortable situation and has to be taken care properly in order to get a well behaved solution for all orders. Now, the remaining coefficients are obtained by using the same procedure as adopted for the evaluation of K_0. The corresponding coefficients are

$$\begin{array}{lcl} K_1 & = & \frac{1}{384}(5sin5t + 45sin3t - 280sint + 120tcost) \\ K_2 & = & \frac{2}{384}(-5cos5t - 15cos3t + 20cost - 120tsint) \\ K_3 & = & \frac{2}{384}(-5sin5t + 15sin3t - 140sint + 120tcost) \\ K_4 & = & \frac{1}{384}(5cos5t - 45cos3t + 40cost - 120tsint) \\ and & & \\ K_5 & = & \frac{1}{384}(sin5t - 15sin3t - 80sint + 120tcost) \end{array} \tag{15}$$

Hence, the first order solution is given by

$$x_1(t) = \sum_{i=0}^{5} K_i x^{5-i}(0)\dot{x}^i(0). \tag{16}$$

Thus the total solution (8) is simply

$$x(t) = x(0)cost + \dot{x}(0)sint + \lambda \sum_{i=0}^{5} K_i x^{5-i}(0)\dot{x}^i(0). \tag{17}$$

Now to have a check of the solution (16), we consider a special case $\dot{x}(0) = 0$ and $x(0) = a$. Hence the total solution reduces to an extraordinarily simple form as

$$x(t) = acost + \frac{\lambda a^5}{384}(cos5t + 15\,cos3t - 16\,cost - 120\,tsint). \tag{18}$$

It is clear that the presence of secular term proportional to $tsint$ makes the life difficult as t grows. We confine

ourselves in the weak coupling regime and we assume C is a constant such that

$$\begin{aligned} sin\,(C\lambda t) &= C\lambda t \\ cos\,(C\lambda t) &= 1 \end{aligned} \quad . \tag{19}$$

Now, the equation (18) is rearranged as

$$x(t) = acos[t(1+\frac{5}{16}\lambda a^4)] + \lambda a^5(-\frac{1}{24}cost + \frac{5}{128}cos3t + \frac{1}{384}cos5t) \tag{20}$$

where the equation (19) is used. Thus the secular term present in the first order solution (18) is summed up for all orders and the frequency shift of the oscillator is obtained. The corresponding frequency shift of the sextic anharmonic oscillator is $\frac{5}{16}\lambda a^4$. The shifted frequency of the oscillator is also viewed as the renormalization of frequency by the anharmonic interaction. Interestingly, the frequency shift obtained in the solution (20) exactly coincides with that obtained by Dutt and Lakshmanan [30]. Now to have an idea of how good the solutions (18) and (20) are we compare them with the exact numerical solution obtained by Mathematica (figure 1). From figure 1, we observe that the first order frequency renormalized solution (20) coincides exactly with the exact numerical solution obtained by using Mathematica (for $a = 2$ and $\lambda = 0.01$). However, the solution (18) diverges with the increase of time (figure 1). The divergent nature of the solution manifests the presence of secular term.



figure1

Now we replace $x(t)$ and $\dot{x}(t)$ with the noncommuting operators $X(t)$ and $\dot{X}(t)$ respectively. Finally, it is

straightforward to generalize the classical solution (8) into a quantum solution of the anharmonic oscillator by the imposition of commutation relation (5). The corresponding solution of the quantum sextic oscillator is given by

$$\begin{aligned}
X(t) &= X(0)cost + \dot{X}(0)sint + \tfrac{\lambda}{384}X^5(0) \times (cos5t + 15\,cos3t - 16\,cost - 120\,tsint) \\
&+ \tfrac{\lambda}{1920}[X^4(0)\dot{X}(0) + X^3(0)\dot{X}(0)X(0) + X^2(0)\dot{X}(0)X^2(0) + X(0)\dot{X}(0)X^3(0) + \dot{X}(0)X^4(0)] \\
&\times (5sin5t + 45sin3t - 280sint + 120tcost) \\
&+ \tfrac{\lambda}{1920}[X^3(0)\dot{X}^2(0) + X^2(0)\dot{X}^2(0)X(0) + X^2(0)\dot{X}(0)X(0)\dot{X}(0) \\
&+ X(0)\dot{X}^2(0)X^2(0) + X(0)\dot{X}(0)X(0)\dot{X}(0)X(0) + X(0)\dot{X}(0)X^2(0)\dot{X}(0) \\
&+ \dot{X}^2(0)X^3(0) + \dot{X}(0)X(0)\dot{X}(0)X^2(0) + \dot{X}(0)X^2(0)\dot{X}(0)X(0) + \dot{X}(0)X^3(0)\dot{X}(0)] \\
&\times (-5cos5t - 15cos3t + 20cost - 120tsint) \\
&+ \tfrac{\lambda}{1920}[\dot{X}^3(0)X^2(0) + \dot{X}^2(0)X^2(0)\dot{X}(0) + \dot{X}^2(0)X(0)\dot{X}(0)X(0) + \dot{X}(0)X^2(0)\dot{X}^2(0) \\
&+ \dot{X}(0)X(0)\dot{X}(0)X(0)\dot{X}(0) + \dot{X}(0)X(0)\dot{X}^2(0)X(0) + X^2(0)\dot{X}^3(0) \\
&+ X(0)\dot{X}(0)X(0)\dot{X}^2(0) + X(0)\dot{X}^2(0)X(0)\dot{X}(0) + X(0)\dot{X}^3(0)X(0)] \\
&\times (-5sin5t + 15sin3t - 140sint + 120tcost) \\
&+ \tfrac{\lambda}{1920}[X(0)\dot{X}^4(0) + \dot{X}(0)X(0)\dot{X}^3(0) + \dot{X}^2(0)X(0)\dot{X}^2(0) + \dot{X}^3(0)X(0)\dot{X}(0) + \dot{X}^4(0)X(0)] \\
&\times (5cos5t - 45cos3t + 40cost - 120tsint) \\
&+ \tfrac{\lambda\dot{X}^5(0)}{384}(sin5t - 15sin3t - 80sint + 120tcost)
\end{aligned} \tag{21}$$

where $X(0)$ and $\dot{X}(0)$ are the initial position and momentum operators. The solution (21) may be written in the symmetrical form as

$$\begin{aligned}
X(t) &= X(0)cost + \dot{X}(0)sint \\
&+ \tfrac{2\lambda}{768}X^5(0)(cos5t + 15\,cos3t - 16\,cost - 120\,tsint) \\
&+ \tfrac{\lambda}{768}[X^4(0)\dot{X}(0) + \dot{X}(0)X^4(0)] \\
&\times (5sin5t + 45sin3t - 280sint + 120tcost) \\
&+ \tfrac{2\lambda}{768}[X^3(0)\dot{X}^2(0) + \dot{X}^2(0)X^3(0) + 3X(0)] \\
&\times (-5cos5t - 15cos3t + 20cost - 120tsint) \\
&+ \tfrac{2\lambda}{768}[\dot{X}^3(0)X^2(0) + X^2(0)\dot{X}^3(0) + 3\dot{X}(0)] \\
&\times (-5sin5t + 15sin3t - 140sint + 120tcost) \\
&+ \tfrac{\lambda}{768}[X(0)\dot{X}^4(0) + \dot{X}^4(0)X(0)] \\
&\times (5cos5t - 45cos3t + 40cost - 120tsint) \\
&+ \tfrac{2\lambda\dot{X}^5(0)}{768}(sin5t - 15sin3t - 80sint + 120tcost)
\end{aligned} \tag{22}$$

The equation (22) is our desired solution for a quantum sextic anharmonic oscillator. Now we rearrange our derived

solution (22) with the help of (19) as

$$\begin{aligned} X(t) &= \tfrac{1}{2}\left\{X(0)cos\left(t+\tfrac{5\lambda t}{4}\left\{H_0^2+\tfrac{1}{4}\right\}\right)+cos\left(t+\tfrac{5\lambda t}{4}\left\{H_0^2+\tfrac{1}{4}\right\}\right)X(0)\right. \\ &+ \dot{X}(0)sin\left(t+\tfrac{5\lambda t}{4}\left\{H_0^2+\tfrac{1}{4}\right\}\right)+sin\left(t+\tfrac{5\lambda t}{4}\left\{H_0^2+\tfrac{1}{4}\right\}\right)\dot{X}(0) \\ &+ \tfrac{2\lambda X^5(0)}{384}(cos5t+15\,cos3t-16\,cost) \\ &+ \tfrac{\lambda}{384}[X^4(0)\dot{X}(0)+\dot{X}(0)X^4(0)](5sin5t+45sin3t-280sint) \\ &+ \tfrac{2\lambda}{384}[X^3(0)\dot{X}^2(0)+\dot{X}^2(0)X^3(0)+3X(0)](-5cos5t-15cos3t+20cost) \\ &+ \tfrac{2\lambda}{384}[\dot{X}^3(0)X^2(0)+X^2(0)\dot{X}^3(0)+3\dot{X}(0)](-5sin5t+15sin3t-140sint) \\ &+ \tfrac{\lambda}{384}[X(0)\dot{X}^4(0)+\dot{X}^4(0)X(0)](5cos5t-45cos3t+40cost) \\ &+ \left.\tfrac{2\lambda\dot{X}^5(0)}{384}(sin5t-15sin3t-80sint)\right\} \end{aligned} \tag{23}$$

where $H_0=\frac{\dot{X}^2(0)}{2}+\frac{X^2(0)}{2}$ is the unperturbed Hamiltonian. Now the first order frequency operator, $\Omega=1+\frac{5\lambda}{4}\left\{H_0^2+\frac{1}{4}\right\}$ coincides exactly with the MSPT results of Pathak [31]. The matrix element $<n-1|X(t)|n>$ and hence the frequency shift of the oscillator may also be calculated with the help of following relations

$$\begin{aligned} H_0|n> &= (n+\tfrac{1}{2})|n> \\ X(0)|n> &= \tfrac{1}{\sqrt{2}}\left[\sqrt{n}|n-1>+\sqrt{n+1}|n+1>\right]\ for\, n\neq 0 \\ \dot{X}(0)|n> &= \tfrac{-i}{\sqrt{2}}\left[\sqrt{n}|n-1>-\sqrt{n+1}|n+1>\right]\ for\, n\neq 0. \end{aligned} \tag{24}$$

From the field theoretic point of view, n may be regarded as the number of photons present in the quantized radiation field. Now, the dipole moment matrix element in terms of the number eigenket $|n>$ is

$$\begin{aligned} <n-1|X(t)|n> &= \tfrac{cos(\frac{5\lambda t}{4}n)}{2}\left\{<n-1|X(0)|n>cos\left(t+\tfrac{5\lambda t}{4}\left\{n^2+\tfrac{1}{2}\right\}\right)\right. \\ &+ cos\left(t+\tfrac{5\lambda t}{4}\left\{n^2+\tfrac{1}{2}\right\}\right)<n-1|X(0)|n> \\ &+ <n-1|\dot{X}(0)|n>sin\left(t+\tfrac{5\lambda t}{4}\left\{n^2+\tfrac{1}{2}\right\}\right) \\ &+ sin\left(t+\tfrac{5\lambda t}{4}\left\{n^2+\tfrac{1}{2}\right\}\right)<n-1|\dot{X}(0)|n> \\ &+ <n-1|\left[\tfrac{2\lambda X^5(0)}{384}(cos5t+15\,cos3t-16\,cost)\right. \\ &+ \tfrac{\lambda}{384}[X^4(0)\dot{X}(0)+\dot{X}(0)X^4(0)](5sin5t+45sin3t-280sint) \\ &+ \tfrac{2\lambda}{384}[X^3(0)\dot{X}^2(0)+\dot{X}^2(0)X^3(0)+3X(0)](-5cos5t-15cos3t+20cost) \\ &+ \tfrac{2\lambda}{384}[\dot{X}^3(0)X^2(0)+X^2(0)\dot{X}^3(0)+3\dot{X}(0)](-5sin5t+15sin3t-140sint) \\ &+ \tfrac{\lambda}{384}[X(0)\dot{X}^4(0)+\dot{X}^4(0)X(0)](5cos5t-45cos3t+40cost) \\ &+ \left.\left.\tfrac{2\lambda\dot{X}^5(0)}{384}(sin5t-15sin3t-80sint)\right]|n>\right\}. \end{aligned} \tag{25}$$

Hence, we obtain the frequency shift of the oscillator as $\frac{5\lambda}{4}(n^2+\frac{1}{2})$. It is interesting to note that the frequency shift of the oscillator is possible even when there are no photons (i.e vacuum field) present in the radiation field. This phenomena is a direct outcome of pure quantum electrodynamic effect and has no classical analog. The frequency shift of the oscillator for a vacuum field is actually a second order effect and is reported elsewhere [27]. The solution (23) is of its first kind and does not have any direct check. However, the frequency shift in (25) may be compared with the frequency shift calculated by using first order perturbation technique [34]. To have a check, we calculate

the energy of a sextic oscillator in $n-th$ energy state which is given by

$$E_n = (n+\frac{1}{2}) + \frac{5\lambda}{48}(4n^3+6n^2+8n+3). \tag{26}$$

The energy difference between two consecutive levels is

$$\Delta E = E_n - E_{n-1} = 1 + \frac{5\lambda}{4}(n^2+\frac{1}{2}). \tag{27}$$

Thus our calculated frequency shift and hence the solution agrees nicely. Finally we normalize the equation (23)with the help of the equation (25) as

$$\begin{aligned}
X(t) &= \tfrac{1}{2cos(\frac{5\lambda t}{4}n)}\left\{X(0)cos\left(t+\tfrac{5\lambda t}{4}\left\{H_0^2+\tfrac{1}{4}\right\}\right)+cos\left(t+\tfrac{5\lambda t}{4}\left\{H_0^2+\tfrac{1}{4}\right\}\right)X(0)\right. \\
&+ \dot{X}(0)sin\left(t+\tfrac{5\lambda t}{4}\left\{H_0^2+\tfrac{1}{4}\right\}\right)+sin\left(t+\tfrac{5\lambda t}{4}\left\{H_0^2+\tfrac{1}{4}\right\}\right)\dot{X}(0) \\
&+ \tfrac{2\lambda X^5(0)}{384}(cos5t+15\,cos3t-16\,cost) \\
&+ \tfrac{\lambda}{384}[X^4(0)\dot{X}(0)+\dot{X}(0)X^4(0)](5sin5t+45sin3t-280sint) \\
&+ \tfrac{2\lambda}{384}[X^3(0)\dot{X}^2(0)+\dot{X}^2(0)X^3(0)+3X(0)](-5cos5t-15cos3t+20cost) \\
&+ \tfrac{2\lambda}{384}[\dot{X}^3(0)X^2(0)+X^2(0)\dot{X}^3(0)+3\dot{X}(0)](-5sin5t+15sin3t-140sint) \\
&+ \tfrac{\lambda}{384}[X(0)\dot{X}^4(0)+\dot{X}^4(0)X(0)](5cos5t-45cos3t+40cost) \\
&+ \left.\tfrac{2\lambda\dot{X}^5(0)}{384}(sin5t-15sin3t-80sint)\right\}.
\end{aligned} \tag{28}$$

The equation (28) is the desired solution for quantum sextic anharmonic oscillator where the secular terms for all orders are summed up.

4 Octic Oscillator.

Depending upon the nature of nonlinearity, the higher anharmonic oscillators will come into picture. For example, octic anharmonic oscillator may be obtained if we put $m=4$ in the equations (6) and (7) respectively. Using the similar procedure (as adopted for sextic oscillator), the solution (up to the linear power of λ) for an octic oscillator follows immediately as

$$\begin{aligned}
x(t) &= x(0)cost+\dot{x}(0)sint \\
&+ \tfrac{\lambda x^7(0)}{3072}(cos7t+14cos5t+126cos3t-141cost-840tsint) \\
&+ \tfrac{\lambda\dot{x}(0)x^6(0)}{3072}(7sin7t+70sin5t+378sint-2373sint+840tcost) \\
&+ \tfrac{\lambda\dot{x}^2(0)x^5(0)}{3072}(-21cos7t-126cos5t-126cos3t+273cost-2520tsint) \\
&+ \tfrac{\lambda\dot{x}^3(0)x^4(0)}{3072}(-35sin7t-70sin5t+630sin3t-3815sint+2520tcost) \\
&+ \tfrac{\lambda\dot{x}^4(0)x^3(0)}{3072}(35cos7t-70cos5t-630cos3t+665cost-2520tsint) \\
&+ \tfrac{\lambda\dot{x}^5(0)x^2(0)}{3072}(21sin7t-126sin5t+126sin3t-2415sint+2520tcost) \\
&+ \tfrac{\lambda\dot{x}^6(0)x(0)}{3072}(-7cos7t+70cos5t-378cos3t+315cost-840tsint) \\
&+ \tfrac{\lambda\dot{x}^7(0)}{3072}(-sin7t+14sin5t-126sin3t-525sint+840tcost)
\end{aligned} \tag{29}$$

To check the validity of our solution, we consider a special case $x(0) = b$ and $\dot{x}(0) = 0$. After a little algebra we have

$$x(t) = bcos(1 + \frac{35\lambda}{128}b^6)t + \frac{\lambda b^7}{3072}(-141cost + 126cos3t + 14cos5t + cos7t). \tag{30}$$

Thus the frequency shift of the classical octic oscillator is proportional to the sixth power of amplitude as long as the first order solution is concerned. The solution (30) as well as the frequency shift have exact coincidence with the solution obtained by the procedure introduced by Bradbury and Brintzenhoff [33]. Now we generalize the solution (29) to have the corresponding quantum solution in the symmetrical form as

$$\begin{aligned}
X(t) &= X(0)cost + \dot{X}(0)sint \\
&+ \tfrac{\lambda X^7(0)}{3072}(cos7t + 14cos5t + 126cos3t - 141cost - 840tsint) \\
&+ \tfrac{\lambda}{6144}[\dot{X}(0)X^6(0) + X^6(0)\dot{X}(0)](7sin7t + 70sin5t + 378sint - 2373sint + 840tcost) \\
&+ \tfrac{\lambda}{6144}[\dot{X}^5(0)X^2(0) + X^2(0)\dot{X}^5(0) + 10X^3(0)\} \\
&\times (-21cos7t - 126cos5t - 126cos3t + 273cost - 2520tsint) \\
&+ \tfrac{\lambda}{6144}[\dot{X}^4(0)X^3(0) + X^3(0)\dot{X}^4(0) + 9(X^2(0)\dot{X}(0) + \dot{X}(0)X^2(0))] \\
&\times (-35sin7t - 70sin5t + 630sin3t - 3815sint + 2520tcost) \\
&+ \tfrac{\lambda}{6144}[\dot{X}^3(0)X^4(0) + X^4(0)\dot{X}^3(0) + 9(\dot{X}^2(0)X(0) + X(0)\dot{X}^2(0))] \\
&\times (35cos7t - 70cos5t - 630cos3t + 665cost - 2520tsint) \\
&+ \tfrac{\lambda}{6144}[\dot{X}^5(0)X^2(0) + X^2(0)\dot{X}^5(0) + 10\dot{X}^3(0)] \\
&\times (21sin7t - 126sin5t + 126sin3t - 2415sint + 2520tcost) \\
&+ \tfrac{\lambda}{3072}[\dot{X}^6(0)X(0) + X(0)\dot{X}^6(0)](-7cos7t + 70cos5t - 378cos3t + 315cost - 840tsint) \\
&+ \tfrac{\lambda\dot{X}^7(0)}{3072}(-sin7t + 14sin5t - 126sin3t - 525sint + 840tcost)
\end{aligned} \tag{31}$$

The problem of secular terms are taken care by the same procedure as it is done in the case of a sextic anharmonic oscillator. The final solution appears as

$$\begin{aligned}
X(t) &= \tfrac{1}{2cos[\frac{35\lambda}{64}(6n^2+3)t]}\Big\{X(0)cos\Omega t + cos\Omega tX(0) + \dot{X}(0)sin\Omega t + sin\Omega t\dot{X}(0) \\
&+ \tfrac{2\lambda X^7(0)}{3072}(cos7t + 14cos5t + 126cos3t - 141cost) \\
&+ \tfrac{\lambda}{3072}[\dot{X}(0)X^6(0) + X^6(0)\dot{X}(0)](7sin7t + 70sin5t + 378sint - 2373sint) \\
&+ \tfrac{\lambda}{3072}[\dot{X}^5(0)X^2(0) + X^2(0)\dot{X}^5(0) + 10X^3(0)] \\
&\times (-21cos7t - 126cos5t - 126cos3t + 273cost) \\
&+ \tfrac{\lambda}{3072}[\dot{X}^4(0)X^3(0) + X^3(0)\dot{X}^4(0) + 9(X^2(0)\dot{X}(0) + \dot{X}(0)X^2(0))] \\
&\times (-35sin7t - 70sin5t + 630sin3t - 3815sint) \\
&+ \tfrac{\lambda}{3072}[\dot{X}^3(0)X^4(0) + X^4(0)\dot{X}^3(0) + 9(\dot{X}^2(0)X(0) + X(0)\dot{X}^2(0))] \\
&\times (35cos7t - 70cos5t - 630cos3t + 665cost) \\
&+ \tfrac{\lambda}{3072}[\dot{X}^5(0)X^2(0) + X^2(0)\dot{X}^5(0) + 10\dot{X}^3(0)] \\
&\times (21sin7t - 126sin5t + 126sin3t - 2415sint) \\
&+ \tfrac{\lambda}{3072}[\dot{X}^6(0)X(0) + X(0)\dot{X}^6(0)](-7cos7t + 70cos5t - 378cos3t + 315cost) \\
&+ \tfrac{2\lambda\dot{X}^7(0)}{3072}(-sin7t + 14sin5t - 126sin3t - 525sint)\Big\}
\end{aligned} \tag{32}$$

where $\Omega = 1 + \frac{35\lambda}{64}(4H_0^3 + 5H_0)$, is the first order frequency operator which is in exact accordance with the frequency operator obtained by Pathak[

]. Now, the matrix element $< n-1|X(t)|n >$ is calculated to obtain the shifted frequency as $\omega^{/} = 1 + \frac{35\lambda}{16}(n^3+2n)$. Interestingly, the frequency shift $\frac{35\lambda}{16}(n^3+2n)$ depends on n^3. It is clear that the vacuum field has no role to play in the frequency shift of the quantum octic oscillator. This is the first time we give the solution of an octic oscillator (32) and therefore, it is not possible to have a direct verification of the solution. However, to have a possible verification of the solution, we calculate the frequency shift by using Rayleigh-Schroedinger perturbation theory. A first order calculation under this theory shows that the energy of the octic oscillator in $n-th$ state is given by

$$E_n = (n + \frac{1}{2}) + \frac{35\lambda}{64}(\frac{3}{2} + 4n + 5n^2 + 2n^3 + n^4). \tag{33}$$

The energy difference between two consecutive levels is $\Delta E = E_n - E_{n-1} = 1 + \frac{35\lambda}{16}(n^3 + 2n)$. Thus, the frequency shift exactly coincides with the frequency shift obtained by us.

5 Remarks and Conclusions:

We obtain analytical solutions (first order) for sextic (8) and octic (29) oscillators in classical pictures by using Taylor series method. The solutions exhibit the presence of usual secular terms. The secular terms for all orders are tucked in to obtain the frequency shifts of those oscillators. It is found that the calculated shifts agree satisfactorily with the shifts obtained by other methods.

The position and momentum of classical oscillators are replaced by their corresponding operators and the commutation relation is imposed. Hence, the solutions for quantum sextic and octic oscillators in the realm of Heisenberg picture is obtained. Interestingly, the vacuum field has no role to play in the frequency shift of the quantum oscillators of quartic and octic anharmonicities. However, the vacuum field causes the frequency shift of a quantum sextic oscillator. These apparent discrepancies are easily understood in terms of field theoretic point of view where the vacuum field effect is considered as a second order one. In fact, the frequency shift due to vacuum field is obtained in a second order solution (i.e solution contains λ^2) of a quantum quartic oscillator [27].

To the best of our knowledge, there only few possible methods available for the purpose of getting analytical solutions of a quantum quartic anharmonic oscillators [20-27]. The method devised by one of us [24] is already tested its usefulness for the purpose of getting an analytical second order solution of a quantum quartic anharmonic oscillator [27]. However, there is no publication till date which deal with the solution of higher anharmonic oscillators. Therefore, the solutions for higher anharmonic oscillators of the present letter will serve a lot of academic interest. In addition to these the solutions will be useful in nonlinear mechanics, molecular physics and in the field theory. In particular, the solutions for quantum anharmonic oscillators are useful to investigate the quantum statistical properties of radiation field. For example, the squeezing effects are reported for a third order nonlinear non-absorbing medium by using the solution of the quantum quartic oscillator [27,35].

The present solutions along with the solutions given by us [24,31] seem to be useful for the purpose of getting a general solution of $m-th$ anharmonicities. Such solutions will be taken care in future publications.

Acknowledgments: *One of the authors (AP) is thankful to the CSIR for the award of a Senior Research Fellow-*

ship. The work is supported by the Department of Science and Technology (SR/SY/P-10/92) and the Council of Scientific and Industrial Research (03/798/96-EMR-II).

References

1. A. H. Nayfeh, Introduction to Perturbation Techniques (Wiley, New York, 1981) p.112.
2. S. L. Ross , Differential Equation 3rd Eds. (John Wiley, New York, 1984) p.707.
3. H. Margenau and G. M. Murphy, The Mathematics of Physics and Chemistry *(*D.Van Nostrand Company, Princeton, 1956*)* p.483.
4. R. Bellman, Methods of Nonlinear Analysis Vol.1 *(*Academic Press, New York, 1970*)* p.198 .
5. C. M. Bender and T. T. Wu, Phys.Rev., 184 (1969) 1231.
6. C. M. Bender and T. T. Wu, Phys.Rev.Lett., 27 (1971) 461.
7. J. J. Loeffel, A. Martin, B. Simon and A. S. Wightman, Phys.Lett 30B (1969) 656.
8. C. M. Bender and T. T. Wu, Phys.Rev D., 7 (1973) 1620.
9. G. A. Arteca, F. M. Fernandez and E. A. Castro, Large order Perturbation Theory and Summation Methods in Quantum Mechanics (Berlin: Springer-Verlag, 1990).
10. P. O. Lowdin (Ed.), Int.J.Quanum.Chem. (1982), (Proceedings of the Sanibel Workshop on Perturbation Theory at Large Order, Sanibel Conference, Florida, 1981)
11. B. Simon, Ann. Phys., A 31 (1970) 76.
12. B. Simon, Int. J. Quantum Chemistry, 21 (1982) 3.
13. S. Graffi, V. Greechi and B. Simon, Phys. Lett., 32B (1970) 631.
14. I. A. Ivanov, J Phys. A, 31 (1998) 5697.
15. E. J. Weniger, Ann.Phys., 246 (1996) 133.
16. E. J. Weniger, J. Cizek and F. Vinette, J. Math. Phys., 39 (1993) 571.
17. F. Vinette and J. Cizek, J. Math. Phys., 32 (1991) 3392.
18. F. Fernandez and J. Cizek, Phys. Lett., 166A (1992) 173.
19. S. Graffi, V. Greechi and G. Turchetti, IL Nuovo Cimento, 4B (1971) 313.
20. S O Aks, Fortsch. der Phys. **15** (1967) 661.
21. S O Aks and Caharat R A, IL Nuovo Cimento **64** (1969) 798.

22. C. M. Bender and L. M. A. Bettencourt, Phys. Rev. Lett., 77 (1996) 4114.

23. C. M. Bender and L. M. A. Bettencourt, Phys. Rev. D, 54 (1996) 7710.

24. S. Mandal, J. Phys. A, 31 (1998) L501.

25. Egusquiza IL and Valle Basagoitti M A, Phys. Rev. A **57** (1998)1586.

26. P B Kahn and Zarmi Y, J. Math. Phys. **40** (1998) 4658.

27. A. Pathak and S. Mandal, Phys. Lett.A **286** (2001) 261

28. M.Lakshmanan and J.Prabhakaran, LETT.NUOVO.CIMENTO 7 (1973) 689.

29. S. N. Biswas, K. Datta, R. P. Saxena, P. K. Srivastava and V. S. Verma, J.Math.Phys, 14 (1973) 1190.

30. R. Dutt and M. Lakshmanan, J.Math.Phys 17 (1976) 482.

31. A Pathak, J. Phys A **33** (2000) 5607.

32. F M Fernandez, J. Phys A **34** (2001) 4851.

33. T. C. Bradbury and A. Brintzenhoff, J.Math.Phys 12 (1971) 1269 .

34. J. L. Powel and B. Crasemann, Quantum Mechanics (Addision-Wesley, Massachusetts, 1961)

35. S. Mandal, J.Phys.B **33** (2000) 1029.